

Error: "PANIC: Boards in same module show different moduleids"

Published 03/07/2000

Symptom(s):

Error: "PANIC: Boards in same module show different moduleids"
Error: "PANIC: Failed to automatically assign moduleids"
Boards in same module show different module IDs
Failed to assign module IDs
system drops into POD mode at power on

Fact(s):

SGI Origin 2000
Silicon Graphics Onyx2

SGI Solution:

At the POD prompt type the following:
pod> go cac
cac> initalllogs *you will be asked for a confirmation to initalllogs? y *
cac> reset

Change(s):

system upgraded from IRIX 6.4 to IRIX 6.5.x

Additional Details

Creation Date	01/06/2000 09:44 AM
Last modification	01/15/2016 04:29 PM
Published Date	03/07/2000
Products	• Servers and Clusters • SGI Origin/Onyx • Origin/Onyx Server • Workstations • SGI Tezro • O2 • Octane
Categories	• Knowledgebase • Technical Solution